Complete illuminated emergency pushbutton BLN



| Technical data | |
|---|--|
| Rated insulation voltage U _i | 500 V |
| Rated continuous current I _u =I _{th} | 10 A |
| Rated operational current I _e for AC-15 | 2.5 A (230 V) 1.6 A (400/500 V) |
| Rated operational current I _e for AC-13 | 4 A (24 V) 1 A (110 V) 0.25 A (220 V) |
| Switch short-circuit protection | 10 A (fast fuse link) 1 kA (prospective short circuit current for $\rm U_e{=}500\rm V)$ |
| Mechanical endurance | 0.3 mln (transposition cycles) |
| Electrical endurance | 0.2 mln (at rated switching voltages and currents) 1.0 mln (switching cycles) - up to 80 VA (for AC electromagnets) - up to 10 W (for DC electromagnets) |
| Frequency of switching | up to 360 h ⁻¹ |
| Ambient temperature | -40 +70°C (work) -40 +70°C (storage) |
| Vibration test (acc. to IEC 60068-2-6) | 213, 2100 Hz (frequency) ± 1 mm (amplitude) ±0.7 g (acceleration) |
| Shock test (acc. to IEC 60068-2-27) | 15 g (peak acceleration) 11 ms (impulse duration) |
| Damp heat cyclic test (acc. to IEC 60068-2-30) | 55°C (ambient temperature) 95% (relative humidity) |
| Salt mist cyclic test (acc. to IEC 60068-2-52) | severity 1 |
| Protection level (Publ. IEC529) of pushbutton actuators after mounting in panel opening | IP65 |
| Wire gauge | $2 \times 12.5 \text{ mm}^2$ (solid) 0.751.5 mm ² (stranded) |
| Working position | any |
| Terminal marking | PN-EN 50013 |
| Lamp power rating | 1.6 W (LED UNI 24-230 V AC and 24-110 V DC) |
| Compliance with the standard | PN-EN 60947-5-1 IEC 60947-5-1 IEC 60947-1 PN-EN 60947-5-5 |

| Switches with effective opening NC | | | |
|--|--------|--|--|
| Minimum travel for effective opening | 6.3 mm | | |
| Maximum travel with end travel | 11 mm | | |
| Minimum force required for effective opening posistion | 35 N | | |

| Accessories | |
|----------------------------------|--|
| Aluminium legend plate SP22-4510 | |

Ordering code

SP22-BLN- -LED UNI

Switches 10, 20, 30, 40 01, 02, 03, 04 11, 12, 13 21, 22 31

Description: the first digit represents the number of normally open circuits, the second digit represents the number of normally closed circuits.

Components Pushbutton actuators Illuminated emergency pushbutton actuator, standard BLN Lighting elements Universal LED, standard Holders Holder SP22-6625 Switches Switches SP22 rail-mounted Standard switches SP22

Diagram

Dimensions

